

What is claimed is:

SP
A
1. A communicative base station switching system of a portable terminal for switching a communicative base station to neighbor base stations while in motion comprising:

a received electric field measuring section for measuring the received electric fields from the communicative base station and the neighbor base stations;

a received electric field memory section for storing received electric field patterns of the communicative base station and two given neighbor stations measured in the received electric field measuring section whenever the communicative base station for communication for the first time is switched over to one of the neighbor base stations;

a received electric field pattern comparing section for comparing the received electric field patterns of the communicative base station having and the two given neighbor stations and the received electric field patterns stored in the received electric field memory section whenever the received electric fields from the communicative base station been in communication with before and the two given neighbor base stations are measured in the received electric field measuring section; and

a base station position acquiring and switching means for acquiring the position of a neighbor station, which the portable terminal is moving toward, in correspondence to a stored received electric field, which

is found in the received electric field pattern comparing section to be identical in pattern with a measured received electric field, and switching the communicative base station over to the pertinent neighbor base station.

2. The communicative base station switching system according to claim 1, wherein when the portable terminal communicates with the communicative base station for the first time, the received electric field pattern comparing section executes the comparison after the received electric field patterns of all the plurality of neighbor base stations have been stored in the received electric field comparing section by switching the communicative base station over to the neighbor base stations.

3. The received base station switching system according to claim 1, wherein when the portable terminal communicates with the communicative base station for the first time while the received electric field patterns of all the plurality of neighbor base stations have not been stored in the received electric field comparing section by switching the communicative base station over to the neighbor base stations, the received electric field measuring section executes the received electric field measurement for switching the communicative base station over to the neighbor base station of the maximum received electric field intensity.

4. The communicative base station switching system according to claim 1, wherein the two given neighbor base stations are either two adjacent base stations or two adjacent but one base stations or two adjacent but two base stations.

5. A communicative base station switching method of a portable terminal for switching a communicative base station to neighbor base stations while in motion comprising:

a step for measuring the received electric fields from the communicative base station and the neighbor base stations;

a step for storing received electric field patterns of the communicative base station and two given neighbor stations measured in the received electric field measuring section whenever the communicative base station for communication for the first time is switched over to one of the neighbor base stations;

a step for comparing the received electric field patterns of the communicative base station having and the two given neighbor stations and the received electric field patterns stored in the received electric field memory section whenever the received electric fields from the communicative base station been in communication with before and the two given neighbor base stations are measured in the received electric field measuring section; and

a step for acquiring the position of a neighbor station, which the portable terminal is moving toward, in correspondence to a stored received electric field, which is found in the received electric field pattern comparing section to be identical in pattern with a measured received electric field, and switching the communicative base station over to the pertinent neighbor base station.

6. A communicative base station switching system of a portable terminal for switching a communicative base station while in motion comprising:

a base station memory section for storing base station position data;

a base station position comparing section for receiving position data from a global positioning system of a mobile body and obtaining and comparing the distances of the base stations from the portable terminal by using the received position data as the position data of the portable terminal; and

a base station frequency switching section for switching the communicative base station of the portable terminal to the neighbor base station closest to the portable terminal according to the result of comparison in the base station position comparing section.

7. A communicative base station switching system of a portable terminal for switching a communicative base station while in motion in which base station position data

Year	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100
1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	